

Our File No. 9281-4653
Client Reference No. FC US02036

IN THE UNITED STATES PATENT AND TRADEMARK OFFICE
APPLICATION FOR UNITED STATES LETTERS PATENT

INVENTOR: Satoshi Hayasaka

TITLE: Force Sense Imparting/Inputting
Apparatus Capable Of Preventing
Oscillation Of Operation Member,
And Imparting Force Sense

ATTORNEY: Gustavo Siller, Jr.
BRINKS HOFER GILSON & LIONE
P.O. BOX 10395
CHICAGO, ILLINOIS 60610
(312) 321-4200

EXPRESS MAIL NO. EV 327 134 707 US

DATE OF MAILING 9/18/03

FORCE SENSE IMPARTING/INPUTTING APPARATUS CAPABLE OF PREVENTING
OSCILLATION OF OPERATION MEMBER, AND IMPARTING FORCE SENSE

BACKGROUND OF THE INVENTION

5 1. Field of the Invention

This invention relates to a force sense imparting/inputting apparatus that can generate a force sense in an operation member operated manually.

2. Description of the Related Art

10 A mechanical inputting apparatus in which an operation member is allowed to rotate or to linearly move by a mechanism is known. In the mechanical inputting apparatus of this kind, frictional force develops between members and operates as resistance force when the operation member is operated.

15 In a force sense imparting/inputting apparatus for generating a force sense by imparting torque or force to an operation member from an electric actuator that is electrically controlled, however, no apparatus is known that generates a force sense such as frictional force in the operation member, and such
20 a force sense imparting/inputting apparatus has been desired.

Therefore, the inventor of this invention has started developing the invention to satisfy the requirement described above and has produced the following prototype in a development stage of the invention.

25 The prototype of the force sense imparting/inputting apparatus in the development stage of the invention includes an operation member capable of operating and rotating in both normal

and opposite directions, such as a rotary knob, an electric actuator capable of imparting torque in both normal and opposite directions to the rotary knob, such as a motor, detection means for detecting an rotating direction and an rotating angle of the rotary knob, and control means for controlling the motor, that is, a CPU, so that force of a predetermined magnitude in the opposite direction to the rotating direction of the operation member can be imparted to the operation member in accordance with the operating direction of the operating member detected by the detection means.

Incidentally, no prior art reference that discloses any description related with the invention has been found up to this date.

SUMMARY OF THE INVENTION

The prototype of the force sense imparting/inputting apparatus described above can cause torque in the direction opposite to the rotating direction of the rotary knob to operate as the resistance force during operation. When the rotary knob rotates even a little in the normal or opposite direction, however, torque in the opposite direction to the rotating direction is imparted to the rotary knob, so that the rotary knob easily oscillates and cannot be kept at halt under a stable state.

In view of the problem described above, the invention aims at providing a force sense imparting/inputting apparatus in which an operation member does not easily oscillate.

To accomplish the object, the invention provides a force sense imparting/inputting apparatus comprising an operation

member capable of operating in both normal and opposite directions,
an electric actuator capable of imparting force in both normal
and opposite directions to the operation member, detection means
for detecting an operating direction and an operating amount of
5 the operation member, and control means for controlling the
electric actuator so that force in the opposite direction to the
operating direction of the operation member can be imparted to
the operation member in accordance with the operating direction
detected by the detection means, wherein the control means is set
10 so that force in the opposite direction to the operating direction
imparted from the electric actuator to the operation member
increases at the start of the operation of the operation member
from 0 to a predetermined upper limit value with the increase of
the operating amount of the operation member on the basis of a
15 predetermined function, the force in the opposite direction to
the operating direction imparted from the electric actuator to
the operation member is kept at the upper limit value during the
operation of the operation member, and the force in the opposite
direction to the operating direction imparted from the electric
20 actuator to the operation member decreases at the finish of the
operation of the operation member from the upper limit value to
0 with the increase of the moving amount of the operation member
in the opposite direction to the operating direction of the
operation member on the basis of the predetermined function.

25 The invention having the construction described above
operates in the following way.

When the operation member is operated, the detection means

detects the operating direction of the operation member and its operating amount. A detection signal corresponding to the operating direction and the operating amount is outputted to the control means. The control means calculates the force in the opposite direction to the operating direction, that is to be imparted to the operation member, on the basis of the operating direction of the operation member and its operating amount, the predetermined function and the predetermined upper limit value, and controls the electric actuator on the basis of this calculation result.

Consequently, the force in the opposite direction to the operating direction imparted to the operation member gradually increases from 0 to the upper limit value at the start of the operation of the operation member on the basis of the predetermined function. The force in the opposite direction to the operating direction imparted to the operation member is kept at the upper limit value during the operation of the operation member. The force in the opposite direction to the operating direction imparted to the operation member operates in this way as the resistance force to the operation member during its operation.

When the operation of the operation member is finished, the force in the opposite direction to the operating direction gradually decreases from the upper limit value to 0 with the increase of the moving amount of the operation member in the opposite direction to the operating direction on the basis of the predetermined function. In consequence, the operation member

stops. In other words, when the operating amount does not increase any more, the operation member is allowed to move in the opposite direction to the operating direction and then to stop by the force in the opposite direction to the operating direction.

5 As described above, according to the invention, the force in the opposite direction to the operating direction imparted from the electric actuator to the operation member is gradually increased from 0 to the upper limit value at the start of the operation of the operation member and when the operation of the
10 operation member is finished, the force in the opposite direction to the operating direction imparted from the electric actuator to the operation member is gradually decreased from the upper limit value to 0 with the increase of the moving amount of the operation member in the opposite direction to the operating
15 direction. Therefore, when the operation is finished before, or at the point at which, the force in the opposite direction to the operating direction imparted to the operation member reaches the upper limit value, the operation member returns to the position at which it has existed before the operation and comes to halt
20 without oscillation. In other words, the operation member according to the invention does not easily oscillate.

 In the invention, the predetermined function described above may well be a linear function having a gradient greater than 0. In the invention having such a construction, setting of the
25 function can be easily made.

 In the invention, the operation member may be arranged in such a fashion as to be capable of rotating in both normal and

opposite directions and the electric actuator may be a motor capable of imparting torque in both normal and opposite directions to the operation member. The invention having such a construction can impart torque to the operation member with a simple
5 construction.

BRIEF DESCRIPTION OF THE DRAWINGS

Fig. 1 shows a construction of a force sense imparting inputting apparatus according to an embodiment of the invention;

Fig. 2 shows a function and an upper limit value set to
10 control means provided to the embodiment shown in Fig. 1;

Fig. 3 shows an example of the operation of the embodiment shown in Fig. 1; and

Fig. 4 shows another example of the operation of the embodiment shown in Fig. 1.

15 DESCRIPTION OF THE PREFERRED EMBODIMENT

A force sense imparting-inputting apparatus according to the invention will be hereinafter explained.

Fig. 1 shows a construction of a force sense imparting/inputting apparatus according to an embodiment of the
20 invention. Fig. 2 is a graph showing a function and an upper limit value set to control means provided to the embodiment shown in Fig. 1. Fig. 3 is a graph showing an example of the operation of the embodiment shown in Fig. 1. Fig. 4 is a graph showing another example of the operation of the embodiment shown in Fig.
25 1.

As shown in Fig. 1, this embodiment includes an operation member so arranged as to be capable of rotating in normal and

opposite directions, such as a rotary knob 1, an electric actuator
for imparting torque to the rotary knob 1 such as a motor 2,
detection means 3 for detecting an operating direction and an
operating amount of the rotary knob 1, that is, a rotating
5 direction and a rotating angle of the rotary knob 1, such as an
encoder or a potentiometer, and control means for controlling the
motor 2 so as to impart torque in the opposite direction to the
rotating direction to the rotary knob 1 in accordance with the
rotating direction of the rotary knob 1 detected by the detection
10 means 3, that is, a CPU 4.

A function 5 and an upper limit value T_{max} ($-T_{max}$) shown
in Fig. 2 are set to the CPU 4 to calculate the torque imparted
to the rotary knob 1. In Fig. 2, a value of the torque in the
opposite direction imparted to the rotary knob 1 when the rotary
15 knob 1 rotates in one direction is a positive value and the value
of the torque imparted to the rotary knob 1 when the rotary knob
1 rotates in the other direction is a negative value.

The function 5 described above is set to a linear function
having a gradient greater than 0. In the case where the rotary
20 knob 1 is operated and rotated in one direction, the torque in
the opposite direction increases at the start of the operation
of the rotary knob 1 from 0 to the upper limit value T_{max} with
the increase of the rotating angle of the rotary knob 1 in one
direction, that is, until the rotary knob 1 is rotated to a rotating
25 angle θ_a in one direction. The torque in the opposite direction
imparted to the rotary knob 1 is kept at the upper limit value
 T_{max} while the rotary knob 1 is operated. When the operation of

the rotary knob 1 is finished, the torque in the opposite direction imparted to the rotary knob 1 decreases from the upper limit value T_{max} to 0 with the increase of the rotating angle of the rotary knob 1 in the opposite direction until the rotary knob 1 is rotated to the angle θ_a in the opposite direction.

Similarly, when the rotary knob 1 is operated and rotated in the opposite direction, the torque in one direction imparted to the rotary knob 1 increases at the start of the operation of the rotary knob 1 from 0 to the upper limit value T_{max} ($-T_{max}$ in Fig. 2) with the increase of the rotating angle of the rotary knob 1 in the opposite direction, that is, until the rotary knob 1 is rotated to a rotating angle θ_a ($-\theta_a$ in Fig. 2) in the other direction, when the rotary knob 1 is rotated in the other direction. The torque in one direction imparted to the rotary knob 1 is kept at the upper limit value T_{max} ($-T_{max}$ in Fig. 2) while the rotary knob 1 is operated. When the operation of the rotary knob 1 is finished, the torque in one direction imparted to the rotary knob 1 decreases from the upper limit value T_{max} to 0 with the increase of the rotating angle of the rotary knob 1 in one direction until the rotary knob 1 is rotated to the angle θ_a in one direction.

The embodiment having the construction described above operates in the following way.

When the rotary knob 1 is operated, the detection means 3 detects the rotating direction and the rotating angle of the rotary knob 1 and outputs detection signals corresponding to the rotating direction and to the rotating angle to the CPU 4. The CPU 4 calculates the force in the direction opposite to the

rotating direction to be imparted to the rotary knob 1 and outputs the control signal corresponding to this calculation result to the motor 2, and the motor 2 operates.

When the rotary knob 1 is operated and rotated in one
5 direction such as when the rotary knob 1 is operated and rotated from an angle θ_1 to an angle θ_4 as shown in Fig. 3, the torque in the opposite direction imparted to the rotary knob 1 gradually increases while the rotary knob 1 rotates from the angle θ_1 to an angle $\theta_2 (= \theta_1 + \theta_a)$. The torque in the opposite direction
10 reaches the upper limit value T_{max} when the rotary knob 1 rotates to the angle θ_2 . While the rotary knob 1 rotates from the angle θ_2 to the angle θ_4 , the torque in the opposite direction imparted to the rotary knob 1 is kept at the upper limit value T_{max} . The torque in the opposite direction imparted in this way to the rotary
15 knob 1 operates as resistance force to the rotary knob 1 during its rotation in one direction. Therefore, the operator feels as if frictional force acted on the rotary knob 1.

When the rotary knob 1 rotates to the angle θ_4 and the operation is finished, the torque in the opposite direction
20 imparted to the rotary knob 1 turns the rotary knob 1 in the opposite direction. While the rotary knob 1 rotates to an angle $\theta_3 (= \theta_4 - \theta_a)$, the torque in the opposite direction imparted to the rotary knob 1 gradually decreases and reaches 0 when the rotary knob 1 rotates to the angle $\theta_3 (= \theta_4 - \theta_a)$. In other words, the
25 rotary knob 1 returns from the angle θ_4 to the angle θ_3 and then stops.

When the rotary knob 1 is operated and rotated in the

opposite direction such as when the rotary knob 1 is rotated from the angle θ_3 to an angle θ_6 as shown in Fig. 4, too, the torque in one direction imparted to the rotary knob 1 gradually increases while the rotary knob 1 rotates from the angle θ_3 to an angle θ_5 ($= \theta_3 - \theta_a$). The torque in one direction reaches the upper limit value T_{\max} ($-T_{\max}$ in Fig. 4) when the rotary knob 1 rotates to the angle θ_5 . While the rotary knob 1 rotates thereafter from the angle θ_5 to the angle θ_6 , the torque in one direction imparted to the rotary knob 1 is kept at the upper limit value T_{\max} ($-T_{\max}$ in Fig. 4). The torque in one direction imparted in this way to the rotary knob 1 operates as resistance force to the rotary knob 1 during its rotation in the opposite direction. Therefore, the operator feels as if frictional force acted on the rotary knob 1.

When the rotary knob 1 rotates to the angle θ_6 and the operation is finished, the torque in one direction imparted to the rotary knob 1 turns the rotary knob 1 in one direction. While the rotary knob 1 rotates to the angle θ_1 ($=\theta_6 + \theta_a$), the torque in one direction imparted to the rotary knob 1 gradually decreases and reaches 0 when the rotary knob 1 rotates to the angle θ_1 . In other words, the rotary knob 1 returns from the angle θ_6 to the angle θ_1 and then stops.

When the rotary knob 1 is continuously switched from the rotation in one direction to the rotation in the opposite direction such as when the rotary knob 1 is operated and rotated in one direction to the angle θ_4 and is then operated and rotated continuously in the opposite direction, the torque in the opposite

direction imparted to the rotary knob 1 gradually decreases from the upper limit value T_{max} to 0 while the rotary knob 1 rotates from the angle θ_4 to the angle θ_3 . Subsequently, while the rotary knob 1 rotates from the angle θ_3 to the angle θ_5 , the torque in one direction gradually increases from 0 to the upper limit value T_{max} (- T_{max} in Figs. 3 and 4).

Similarly, when the rotary knob 1 is continuously switched from the rotation in the opposite direction to the rotation in one direction such as when the rotary knob 1 is operated and rotated in the other direction to the angle θ_6 and is then operated and rotated continuously in one direction, the torque in one direction imparted to the rotary knob 1 gradually decreases from the upper limit value T_{max} (- T_{max} in Figs. 3 and 4) to 0 while the rotary knob 1 rotates from the angle θ_6 to the angle θ_1 . Subsequently, while the rotary knob 1 rotates from the angle θ_1 to the angle θ_2 , the torque in the opposite direction gradually increases from 0 to the upper limit value T_{max} .

This embodiment provides the following effects.

In this embodiment, the torque in the opposite direction to the operating direction, that is imparted from the motor 2 to the rotary knob 1, is gradually increased from 0 to the upper limit value at the start of the operation of the rotary knob 1 with the increase of the rotating angle of the rotary knob 1 in the same direction as its operating direction, and the torque in the opposite direction to the operating direction, that is imparted from the motor 2 to the rotary knob 1, is gradually decreased from the upper limit value to 0 with the increase of the rotating angle

opposite to the operating direction of the rotary knob 1 at the end of the operation. Therefore, when the operation is finished before, or at the point at which, the torque in the opposite direction to the operating direction imparted to the rotary knob 1 reaches the upper limit value, the rotary knob 1 returns to the angle at which it has existed before the operation, and stops without oscillation. In other words, the rotary knob 1 in the invention does not easily oscillate and hence, the rotary knob 1 can be kept at halt under the stabilized state.

10 In the embodiment, the function 5 for calculating the torque to be imparted to the rotary knob 1 is set to the linear function having the gradient greater than 0. Therefore, the function can be easily set to the CPU 4.

 Although the predetermined function is the linear function 15 5 having the gradient of greater than 0 in this embodiment, the invention is not particularly limited thereto. In other words, the function may well be such that the torque in the opposite direction reaches the upper limit value T_{max} when the rotating angle of the rotary knob 1 in one direction shown in Fig. 2 reaches the angle θ_a , and the torque in one direction reaches the upper limit value T_{max} ($-T_{max}$) when the rotating angle of the rotary knob 1 in the opposite direction reaches θ_a ($-\theta_a$).

 In this embodiment, the electric actuator is the motor. However, the invention is not limited to the motor but may be 25 applied to those electric actuators that operate by electric signals and can impart the torque to the rotary knob 1.

 The embodiment described above employs the construction in

which the torques in the operating direction and the opposite direction are imparted to the rotary knob 1 capable of rotating both normally and oppositely, but the invention is not limited thereto. In other words, when the force sense imparting inputting
5 apparatus equipped with the operation member capable of linearly operating in both normally and oppositely is constituted, the force in the opposite direction to the operating direction may well be imparted to the operation member.

As explained above, the invention gradually increases the
10 force in the opposite direction to the operating direction given from the electric actuator to the operation member from 0 to the upper limit value with the increase of the operating amount at the start of the operation, and gradually decreases the force at the finish of the operation from the upper limit value to 0 with
15 the increase of the movement amount in the opposite direction to the operating direction of the operation member. Therefore, when the operation is finished before, or at the point at which, the force in the opposite direction to the operating direction imparted to the operation member reaches the upper limit value,
20 the operation member returns to the position at which it has existed before the operation and stops there without oscillation. In other words, the operation member does not easily oscillate and hence, can be kept at halt under the stabilized state.